

# Conventional Fire Alarm System 2166 Series

**AW-CMC2166-1**



**AW-CMC2166-5**



**AW-CMC2166-6**



Product Name	Emergency Break Glass	Manual Call Point	Manual Pull Station
Model No.	AW-CMC2166-1	AW-CMC2166-5	AW-CMC2166-6
Operating Voltage	220VAC/50Hz or 24VDC		9~28VDC Volts
Operating Current	Max. Current:5A (220VAC/50Hz) or 8A(24VDC)		Alarm Current: 45mA@ 24 VDC
Contact Resistance	≤0.1 Ω	≤0.02 Ω	5.6K
Working Condition	Temperature: -10℃ to 50℃; Humidity: 10% to 93%, Non-Condensation		



**AW-GSM100**



**AW-EL2166**

Product Name	GSM Module
Model No.	AW-GSM100
Function	Send SMS in the event of Fire or faults to conventional fire alarm control panel.
Input Voltage	DC9V~12V
Standby Current	<55mA
Alarm Current	<450mA
Alarm Loudness	110dB

Product Name	Entrance LED
Model No.	AW-EL2166
Function	To be used with detectors; One 8mm LED provide local 360° visible alarm indication. They flash with the same as detector that be connected.
Performance Feature	2-Wire, Remote LED; Red Color